



TOOLS & EQUIPMENT ■ SUPPLIES ■ SAFETY PRODUCTS ■ TOOL REPAIR ■ RENTALS

Item P12-1194

Circuit Seeker/Circuit Tracer

This tool features superior sensitivity and functionality providing for accurate tracing and locating. Tracing feedback is provided by both audible feedback and graphic display. Traces concealed wiring, locates junction boxes, and finds breakers for live or open circuits. Can be used on GFCI protected circuits, and does not affect sensitive electronic equipment on the circuit.

Operating Conditions:

Temperature: 0 to +50 °C (32 to 122 °F)

Altitude: 2000 m (6500') maximum

Pollution Degree: 2

Indoor use only

Transmitter

Measurement Category: Category III, 750V

Operating Voltage: 0-750 V AC/DC

Live line LED indicates voltage above 12 VAC or 5 VDC

Frequency: 15.15 kHz

Low battery indicator

Batteries: Two AA batteries (NEDA 15A or IEC LR6)

Receiver

Range from Receiver to item with Signal:

Live Line Mode – up to 20 ft (6 m) from circuit

Open Line Mode – Up to 10 ft. (3 m) with a metallic connection to ground.

1 to 3 ft. (.3 to .9 m) with a capacitive ground reference.

Model #	CS-8000
----------------	---------

Item	Description	Attributes
12-1194		